

Notice



- ☐ CORRECTION
 ☒ PRODUCTION CHANGE
☐ SERVICE FLASH
 ☐ ADD INFORMATION

FILE NO.

REVISION 0

Please add this notice to the Service Manual listed below.

Category: **COLOR TELEVISION** Date: **NOVEMBER / 03 / 2009**
 Model: **DP42849** Effective from : Chassis No. **P42849-05**
 Destination: **U.S.A. / CANADA** REF : **No. SM780157-05**

NOTE: Match the Chassis No. on the unit's back cover with the Chassis No. in the Service Manual. **If the Service Manual Chassis No. does not match the unit's**, additional Service Literature is required. This chassis is similar to Chassis No. P42849-00. Only the **difference** Service Information is given in this manual. For detailed Service Information, refer to the **Original** Service Manual and **Notices** for Chassis No. PP42849-00 used in Model DP42849 (SM780157).

SERVICING SHOULD BE PERFORMED BY ONLY TRAINED AND QUALIFIED SERVICE PERSONNEL.

1. IN THE SERVICE ADJUSTMENTS

PAGE 4 ON-SCREEN SERVICE MENU

Item No. **088 OP2 Data** should be changed from **24h** to **23h** in the table and in Note 2.

2. IN THE CHASSIS ELECTRICAL PARTS LIST MISCELLANEOUS

The reason for change.

- A : Misprint B : Quality Reliability C : Standardization
 D : Design E : Add as a possible sub F : Schematic location change
 G : Purchasing Request

Page & Section	Schematic Location		Part No.	Description	Q'ty	Interchangeability	Reason
Page 9, Chassis Electrical Parts List	C1672	Old	CEXLB1V471VDN	ELECT 470U M 35V	1	NO	D
		New	N/A	NOT USED	0	NO	
	C1674	Old	CE1E102MZVANN	ELECT 1000U M 25V	1	NO	D
		New	N/A	NOT USED	0	NO	
	C1675	Old	CK1H104KLZBNG	CERAMIC 0.1U K 50V	1	NO	D
		New	N/A	NOT USED	0	NO	
	C1807	Old	N/A	NOT USED	0	NO	D
		New	CK0J106KGMBNG	CERAMIC 10U Z 6.3V	1	NO	

Page & Section	Schematic Location		Part No.	Description	Q'ty	Interchangeability	Reason
Page 9, Chassis Electrical Parts List	C1814	Old	N/A	NOT USED	0	NO	D
		New	CK1H104KLZBNG	CERAMIC 0.1U K 50V	1	NO	
Page 11 Chassis Electrical Parts List	C6108	Old	CEXLB0J102VDN	ELECT 1000U M 6.3V	1	NO	D
		New	N/A	NOT USED	0	NO	
Page 12 Chassis Electrical Parts List	D1670	Old	DDSS3P3-E3--G	DIODE SS3P3-E3/84A	1	NO	D
		New	N/A	NOT USED	0	NO	
	D1800	Old	DD1SS352----G	DIODE 1SS355-TE-17	1	NO	D
		New	N/A	NOT USED	0	NO	
Page 20 Chassis Electrical Parts List	▲ EL901	Old	1AV4T40C05500	LCD(LC420WUN-SBA1)	1	NO	D
		New	1AV4T40C16800	LCD(T420HW04 V003)	1	NO	
Page 12 Chassis Electrical Parts List	IC1670	Old	QLA5774MPE--P	IC LA5774MP-DL-E	1	NO	D
		New	N/A	NOT USED	0	NO	
	L1606	Old	1LB4L26B0740G	INDUCTOR, 220 OHM	1	NO	D
		New	N/A	NOT USED	0	NO	
Page 13 Chassis Electrical Parts List	L1670	Old	RGFR000ZTAANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	D
		New	N/A	NOT USED	0	NO	
	L1671	Old	RGFR000ZTAANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	D
		New	N/A	NOT USED	0	NO	
	L1674	Old	1AV4L2JJ470KN	INDUCTOR, 47U K	1	NO	D
		New	N/A	NOT USED	0	NO	
	L1676	Old	RGFR000ZTAANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	D
		New	N/A	NOT USED	0	NO	
	L1677	Old	RGFR000ZTAANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	D
		New	N/A	NOT USED	0	NO	
	L1678	Old	N/A	NOT USED	0	NO	D
		New	RGFR000ZTCANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	
	L1679	Old	N/A	NOT USED	0	NO	D
		New	RGFR000ZTCANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	
	L1801	Old	N/A	NOT USED	0	NO	D
		New	1LB4L26B0740G	INDUCTOR, 220 OHM	1	NO	

Page & Section	Schematic Location		Part No.	Description	Q'ty	Interchangeability	Reason
Page 13, Chassis Electrical Parts List	L6103	Old	1AV4L2FB3R3MG	INDUCTOR, 3.3U M	1	NO	D
		New	N/A	NOT USED	0	NO	
	L6104	Old	N/A	NOT USED	0	NO	D
		New	RGFR000ZTAANL	MT-GLAZE 0.000	1	NO	
Page 14, Chassis Electrical Parts List	Q1670	Old	T2SC3928A1R-P	TR 2SC3928A1S	1	NO	D
		New	N/A	NOT USED	0	NO	
Page 16, Chassis Electrical Parts List	R1670	Old	RGF47R0JT CANL	MT-GLAZE 47 JA	1	NO	D
		New	N/A	NOT USED	0	NO	
	R1671	Old	RGF1001FT CANL	MT-GLAZE 1K FA 1/10W	1	NO	D
		New	N/A	NOT USED	0	NO	
	R1672	Old	RGF1002FT CANL	MT-GLAZE 10K FA 1/10W	1	NO	D
		New	N/A	NOT USED	0	NO	
	R1673	Old	RGF1001FT CANL	MT-GLAZE 1K FA 1/10W	1	NO	D
		New	N/A	NOT USED	0	NO	
	R1674	Old	RGF2202JT CANL	MT-GLAZE 22K JA	1	NO	D
		New	N/A	NOT USED	0	NO	
	R1831	Old	1LB4L26B0700G	INDUCTOR, 120 OHM	1	NO	D
		New	RGFR000ZT CANL	MT-GLAZE 0.000	1	NO	
	R1834	Old	CK1A105KLZBNG	CERAMIC 1U K 10V	1	NO	D
		New	N/A	NOT USED	0	NO	
	R1835	Old	N/A	NOT USED	0	NO	D
		New	RGF1002JT CANL	MT-GLAZE 10K JA 1/10W	1	NO	
	R1839	Old	RGF4701JT CANL	MT-GLAZE 4.7K JA 1/10W	1	NO	D
		New	N/A	NOT USED	0	NO	
	R1842	Old	RGF2201JT CANL	MT-GLAZE 2.2K JA 1/10W	1	NO	D
		New	RGF4701JT CANL	MT-GLAZE 4.7K JA 1/10W	1	NO	
	R1855	Old	RGF1000JT CANL	MT-GLAZE 100 JA 1/10W	1	NO	D
		New	N/A	NOT USED	0	NO	
Page 18, Chassis Electrical Parts List	R6323	Old	RGFR000ZT CANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	D
		New	N/A	NOT USED	0	NO	

Page & Section	Schematic Location		Part No.	Description	Q'ty	Interchangeability	Reason
Page 18, Chassis Electrical Parts List	R6333	Old	N/A	NOT USED	0	NO	D
		New	RGFR000ZTCANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	
	R6346	Old	N/A	NOT USED	0	NO	D
		New	RGFR000ZTCANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	
	R6347	Old	N/A	NOT USED	0	NO	D
		New	RGFR000ZTCANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	
Page 15, Chassis Electrical Parts List	R839	Old	N/A	NOT USED	0	NO	D
		New	RGFR000ZTCANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	
	R840	Old	RGFR000ZTCANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	D
		New	N/A	NOT USED	0	NO	
	R841	Old	RGFR000ZTCANL	MT-GLAZE 0.000 ZA 1/10W	1	NO	D
		New	N/A	NOT USED	0	NO	
	R842	Old	N/A	NOT USED	0	NO	D
		New	RGF4701JTCANL	MT-GLAZE 4.7K JA 1/10W	1	NO	
	R843	Old	N/A	NOT USED	0	NO	D
		New	RGF4701JTCANL	MT-GLAZE 4.7K JA 1/10W	1	NO	
	R844	Old	RGF4701JTCANL	MT-GLAZE 4.7K JA 1/10W	1	NO	D
		New	N/A	NOT USED	0	NO	
Page 20, Chassis Electrical Parts List	▲ U901	Old	1AV4U20C39200	UNIT, POWER	1	NO	D
		New	1AV4U20C41501	UNIT, POWER	1	NO	
	▲ WK5L-K7L	Old	1AA4W30B55900	CORD 42INCH,40P-51P(LVDS)	1	NO	D
		New	1AA4W30B55800	CORD 42INCH,40P-51P(LVDS)	1	NO	

For parts or service contact:

Sanyo Manufacturing Corporation
P.O. Box 2000
3333 Sanyo Road
Forrest City, Arkansas 72335-2000

November 2009 SMC

Published in Mexico

DP42849, N7AFE, PRODUCT CODE 113018204

REFERENCE No. SM780157-05